



BLCA3X1

Blast Chiller/Freezer GN1/1

Product Features

- Touch screen controller
- Programmable thermostat
- HACCP compliant data export
- Guides for GN1/1 and Euronorm pans
- Stainless steel
- Core sensor included
- Reversible self-closing door
- Adjustable legs

Blast chiller/freezer with touch screen controller

Our blast chiller/freezer range is perfect for quickly cooling or freezing hot food from the stove or oven, preserving the food in a safe way. The BLCA-X comes with an easy-to-use touch screen controller. Here you can choose one of the pre-set programs for different purposes or you can create and save your own programs. Primary programs are pre-set to keep the end temperature fixed until the cabinet is opened and the program is turned off. This method ensures the quality and safe preservation of the food and makes sure the food is safe for storage and later consumption. Cooling capacity is measured from +70 to +3 °C in 90 minutes - Freezing capacity is measured from +70 to -18 °C in 240 minutes. Exact kg capacity for each model can be found under the technical specifications. The BLCA-X accepts both gastronorm 1/1 and euronorm pans (not included).

Measures and Content

Capacity Cooling	kg	12
Capacity Freezing	kg	8
Capacity GN Pans	pcs	3 x GN1/1
Temperature Range	°C	-18 to +70 / +3 to +70
Climate Class		4
Gross / Net Weight	kg	130 / 104
Gross / Net Volume	l	139 / 60

Design and Material

Door No & Type	1 hinged self-closing solid door	
Door Reversible		Yes
Feet / Legs		4 adjustable feet
Exterior Finish		SS304
Interior Finish		SS304
Interior Light		No
Lock		No

Cooling and Functions

Type of Cooling		Blast
Type of Defrost		Automatic, hot gas
Refrigerant		R290
Refrigerant Charge	g	130

Power and Consumption

Input Power	W	700
Voltage / Frequency	V/Hz	220-240/50
Noise Level	dB(A)	60

Dimensions

Internal Dimension (WxDxH)	mm	660 x 640 x 330
External Dimension (WxDxH)	mm	804 x 826 x 995
Packed Dimension (WxDxH)	mm	870 x 900 x 1030
40ft Container Load	pcs	52



Core sensor included



Touch screen controller